

FRIESEN ELECTRIC INC

AUTHORIZED WHOLESALERS FOR: Penn-Johnson Controls; S&S Sprechersuh Controls; Ferraz - Fuses and Devices; Winpower Generators; Electronic Bug Zappers; Electric Heating Products; Leviton Wiring Products; Reversomatic & Delhi Blowers and Fans; Magnatek AO Smith Electric Motors; F & G line Gear Reducers; Emerson - White Rogers; AC Tech speed controls; Burgess sensors & switches

56C Helical Gear Reducers

AGMA CLASS I

(SERVICE FACTOR 1.0)-1750 INPUT RPM

ARPX. OUT-PUT RPM	BASIC UNIT SIZE											
	1/6 HP	1/4 HP	1/3 HP	1/2 HP	3/4 HP	1 HP	1 1/2HP	2 HP	3 HP	5 HP	7 1/2HP	10 HP
350	25	25	25	25	25	25	25	25	-	-	-	-
232	25	25	25	25	25	25	25	25	-	-	-	-
175	25	25	25	25	25	25	25	25	-	-	-	-
140	25	25	25	25	25	25	25	-	-	-	-	-
116	25	25	25	25	25	25	-	-	-	-	-	-
88	25	25	25	25	25	25	-	-	-	-	-	-
70	25	25	25	25	25	25	-	-	-	-	-	-
58	25	25	25	25	25	-	-	-	-	-	-	-
44	25	25	25	25	25	-	-	-	-	-	-	-
35	25	25	25	25	-	-	-	-	-	-	-	-
29	25	25	25	-	-	-	-	-	-	-	-	-
21.8	25	25	25	-	-	-	-	-	-	-	-	-
17.5	25	25	25	-	-	-	-	-	-	-	-	-
14.5	25	25	-	-	-	-	-	-	-	-	-	-
11.6	-	-	-	-	-	-	-	-	-	-	-	-
9.7	-	-	-	-	-	-	-	-	-	-	-	-

up to 40% more Efficient than Worm Reducers

- Superior to Worm Reducers
- Energy Saving/Efficient
- Oil Sight Glass
- Horizontal or Vertical Applications
- Hardened Gears
- Motorized or Input Shaft



Size 25

Part Number: 4000010015HQD	Ratio: 20 - 1	Frame: 56C
Part Number: 4000010003HQD	Ratio: 25 - 1	Frame: 56C
Part Number: 4000010004HQD	Ratio: 30 - 1	Frame: 56C
Part Number: 4000010006HQT	Ratio: 60 - 1	Frame: 56C

TOLLFREE TEL: 1-800-663-9414
TOLLFREE FAX: 1-888-663-9414

EMAIL: sales@friesen.com
WEB SITE: www.friesen.com